

Delock Converter 3G-SDI > DVI

Description

This Delock converter can be used to convert an HD- or 3G-SDI signal to a DVI signal. You can connect e. g. a camera with HD-SDI output to a DVI monitor. The audio signal can be played via a digital Toslink or RCA output. The SDI signal is transmitted via a conventional 75 Ohm coaxial cable with BNC connectors.



Item no. 93247

EAN: 4043619932474

Country of origin: China

Package: Box

Technical details

- Connector:
 - Input: 1 x BNC female (SDI)
 - Output: 1 x BNC female (SDI, pass-through)
 - 1 x DVI-D 24+5 female
 - 1 x Toslink S/PDIF
 - 1 x RCA S/PDIF
 - 1 x DC Power 5 V
- Supported resolution:
 - SD 480i, 525i und 625i
 - HD 720p 24, 25, 30, 50 und 60 Hz
 - HD 1080i 50, 60 Hz
 - HD 1080p 24, 25, 30, 50 und 60 Hz
- Supported data rate: 270 Mb/s ~ 2.97 Gb/s
- Supports 8 channels of 48 kHz audio (PCM)
- Robust metal housing
- Power consumption: max. 2 W
- Dimensions (LxWxH): ca. 120 x 100 x 25 mm

Power supply specification

- Wall power supply
- Input: AC 100 ~ 240 V / 50 ~ 60 Hz / 0.5 A
- Output: 5 V / 2 A
- Ground outside, plus inside
- Dimensions:
 - inside: ø ca. 2.1 mm
 - outside: ø ca. 5.5 mm
 - length: ca. 9 mm

Package content

- 3G-SDI > DVI Converter
- Mounting brackets and screws
- Power supply 5 V

Images

