



Hubs

Repeater

2 x FireWire B to 1 x GOF

Description

The Delock repeater by IOI extends a FireWire B connection. With the GOF port you can reach a connection of 500 m when you connect two repeater with each other. You get other connection possibilities if your PC or camcorder already got a GOF port. You can connect several FireWire devices like e.g. external enclosures, digital cameras, camcorder, adapter etc. to the repeater.

Images



Ref.	61670
EAN	4043619616701
Country of origin	Taiwan
Customs tariff number	85176200

Specification

- IOI item number: FWB2GOF01-LC
- Connection:
 - 2 x FireWire B (IEEE 1394b) Port with jack screw holes
 - 1 x GOF (Glass Optical Fibre) Port with LC-Duplex connector
- Chipset: Texas Instruments TSB81BA3
- Supports Gigabit Ethernet 850 nm VCSEL
- Data transfer rate up to 800 Mb/s
- Voltage DC: 8 V~33 V, max. 2 A
- Power connector: 2 mm DC Jack Walkman type
- LED indicator for power und link
- Electrical power < 3 Watt
- Working temperature: 10 °C- 40 °C
- Relative humidity: 10 % - 85 % (noncondensing)
- Dimension (LxWxH): 9.3 cm x 6.2 cm x 2.1 cm

System requirements

- One free FireWire B port

Package content

- FireWire B repeater
- 3 screws, power supply, power cord

Package

- White box